WarmlyYours
Radiant Heating Systems
Experts since 1999

INSTALLATION GUIDE

For TWS1 Series hardwired towel warmers.

TOOLS REQUIRED



INSTRUCTIONS

Before using this product, please read the following instructions carefully and keep this pamphlet for future reference.

ABOUT THE PRODUCT:

This heated towel warmer is designed for drying/warming towels or clothes, it has a surface stabilized temperature of 122-131ºF, and it is used in household bathrooms and kitchens, as well as in hotels and restaurants or other public areas. This appliance uses a voltage of 120 VAC, and is manufactured according to cULus standards.

SAFETY PRECAUTIONS:

1. The towel warmer must be used with a Ground Fault Circuit Intercepter (GFCI) circuit.
2. This product is supplied with a three-prong plug or three-wire cable.
   To avoid unnecessary risk or danger, this product must be properly grounded.
3. Any repairs must be done by a qualified technician who is deemed qualified by industry standards. When any external wire fittings are required, the unit must be disconnected from the circuit.

WARNING:

1. Only use for drying textiles which have been dampened by water.
2. If heating wire is damaged, the whole product should be replaced.

NOTE:

1. In the event of any difference in technical specifications, please refer to the actual product.
2. Please wipe the towel rail with a soft, dry cloth when cleaning it.
   Do not use scrubbers or abrasive cleaners.

ACCESSORIES FOR SQUARE/ROUND MOUNTING TUBES



Installation Fittings:
(1+2): Mounting tubes (4 pieces) & Set screws (4 pieces)
(3) 4 brackets (3 pieces)
(4) Short mounting screws (3 pieces) Long mounting screw (1 piece)
(5) Drywall anchor (3 pieces)
(6) Long screws (3 pieces)
(7) Set screws (2 pieces)

This product must be installed in accordance with the instructions in the manual and the NEC and CEC guidelines relating to electrical fixtures in bathrooms. **The Towel Warmer must be on a GFCI protected circuit and be wired by a professional who is certified to do electrical wiring.**

In order to reduce electrical shock, this towel warmer should be installed on a 15A GFCI protected branch circuit (14AWG) and to an outlet box that is 4 inches (10.16 cm) high by 2 Inches (5.08 cm) wide.

WarmlyYours
Radiant Heating Systems
Experts since 1999

INSTALLATION GUIDE

For TWS1 Series hardwired towel warmers.

ACCESSORIES



INSTALLATION: (WARNING: The electrical connection should avoid all water.)

Please refer to all the following steps if the wall brackets are taken apart from the vertical bars.

Please refer to Steps 5-12 if the wall brackets are fixed on vertical bars already.



STEP 1: As shown in the picture, insert the short mounting screw (d) through the tube in the center of the mounting tube (a).



STEP 2: Use the short mounting screw (d) to fix the mounting tube (a) to the threaded metal pad on the vertical bar on the back of the towel warmer.



STEP 3: Screw down the short mounting screw (d) with a screwdriver. Note that the set screw of the tube (a) should point towards the floor when the towel warmer is wall mounted. Fix the remaining two mounting tubes (a) to the vertical bars with threaded metal pads by repeating Step 1-3.



STEP 4: Guide the electrical cord through the electrical connection mounting tube (b) and use the long mounting screw (e) to tighten the electrical connection mounting tube to the vertical bar.

WarmlyYours
Radiant Heating Systems
Experts since 1999

INSTALLATION GUIDE

For TWS1 Series hardwired towel warmers.



STEP 5: Use a tape measure to measure the distance between the center points of each wall bracket tube; record the distances between points AB, AC, CD, and BD. Mounting point C will determine electrical box location. See Electrical Assembly in following instructions.



STEP 6: Mark A, B, C, and D according to the data from Step 5; It is suggested that this product be installed at least 23.5 inches (59.69 cm) above floor level. (WARNING: The electrical connection should avoid all water). This mounting location must comply with all local building and electrical codes.

ALTERNATIVE TO STEPS 5 & 6



Place towel warmer on the box (or a large sheet of paper) and lay on a flat surface with mounting tubes facing downwards. Mark the location of the following:

- The electrical collar (hardwired model only)
- The location of the mounting tubes

Use the template as a guide to mark the wall with the correct locations of the four mounting tubes (A, B, C, and D)



STEP 7: Drill A, B, C, and D holes with an appropriately sized bit. Use a hammer to knock plastic drywall anchor (f) into wall completely.



STEP 8: Insert long screw (i) through mounting bracket (g), then screw into plastic drywall anchor (f).



STEP 9: Install the tube (a) onto the bracket (g).



STEP 10: As shown in the picture, install the set screws (c) into the hole of all the tubes (a) using the allen wrench; fix the tube (a) onto the mounting bracket (g).



STEP 11: Install shelf (k) by inserting the shelf's mounting tube on to the bracket and tighten by inserting the set screw (L) into the hole.

WarmlyYours
Radiant Heating Systems
Experts since 1999

INSTALLATION GUIDE

For TWS1 Series hardwired towel warmers.

ELECTRICAL ASSEMBLY





CAUTION:
To provide continued protection against risk of electric shock, connect to properly grounded outlets only.



2" x 4" ELECTRICAL BOX

Important Notice for Québec Consumers: WarmlyYours does not provide repair services for this product. We offer replacement hardware kits (mounting brackets, screws, installation accessories) and on/off switches, but the heating element (main heating component) is not available as a replacement part. If your towel warmer fails within the warranty period, we will replace the entire unit according to our warranty policy. Our technical support team is available 24/7 by phone for installation and trouble-shooting assistance. For full details, see our Return Policy. This notice is provided in accordance with Québec's Consumer Protection Act, section 39 (as amended in 2025).

WarmlyYours
Radiant Heating Systems
Experts since 1999

INSTALLATION GUIDE

For TWS1 Series hardwired towel warmers.

ACCESSORIES



HARDWARE KIT BY MODEL

Model	Model SKU	Hardware kit
Maui, Polished	TWS1-MAU07PH	AK15-59820-0003
Vancouver, Polished	TWS1-VNC06PH	AK15-59820-0003

REPLACEMENT PARTS

Order a complete hardware kit, or a single part by its part number. Letters match the Accessories diagram on page 2. Parts and support: (800) 875-5285.

ID	Part number	Description	Qty
a	0015-59120-0005	Tube, mounting, square, stainless, polished, 60mm x 25mm	3
b	0015-59120-0006	Tube, power mounting, square, stainless, polished, 60mm x 25mm	1
c	0015-59220-0000	Screw, set, allen, socket, M5x5mm	2
d	0015-59220-0001	Screw, leg mounting, short, phillips, round, M5x10mm	3
e	0015-59220-0002	Screw, leg mounting, long, phillips, round, M4x15mm	1
f	0015-59590-0000	Anchor, wall, #8	3
g	0015-59190-0000	Bracket, round, mounting, welded, 20mm diameter	3
h	PK15-59820-0000	Wallplate Assy., stainless, polished, 4 1/2 x 2 11/16, 20mm tube	1
i	0015-59290-0000	Screw, bracket mounting, phillips, round, M4x30	3
j	0015-59220-0003	Screw, stainless, wallplate, flat, #6x1	2
L	0015-59220-0007	Screw, set, allen, socket, flat, M5x4mm	4
n/s	0015-59890-0001	Wire Nut, orange, UL/CSA	3
n/s	0015-59990-0000	Wrench, hex, 2.5mm	1
n/s	SK15-59020-0000	Towel Warmer Switch, power w/sleeve, o-ring, STW	1

n/s: not shown in the diagram.